





UNIVERSAL PROCESS CONTROLLER UC-820

DESCRIPTION


The UC-820 is a digital universal controller used in the automation of industrial processes. It is ideally suited for use with our range of instrumentation, electric and pneumatic control valves and other electrical equipments.


The controller includes a set of universal type inputs for RTD, thermocouple (TC), logic (binary) and analog inputs. The controller has options for relay, open-collector (OC) and analog outputs using the innovative SMART PID algorithm.

MAIN FEATURES

- Universal measuring input: Resistance thermometer (RTD), thermocouples (TC), 0/4...20 mA and 0...5/10 V.
- · Binary input control.
- Set point value: constant, programmed or from the additional analog input.
- On/off, PID, PID three-step and two-step control (valve control) or PID of heating-cooling type.
- 2 NO relay outputs and 2 other outputs of choice between relay, OC or analog outputs (0/4...20 mA or 0...10 V).
- · Soft-start function.
- 8 types of alarm functions.
- 24 V dc loop power supply output.
- · Signal retransmission.
- "Gain scheduling" function.
- Timer function.
- Auto-tuning using the smart PID algorithm.
- Measurement of heating current and monitoring of heater overheating or shortening of the control element.
- · Galvanically isolated inputs and outputs.
- Password protection.
- Fully programmable from the front panel.
- RS-485 Modbus RTU communication.
- Degree of protection IP65.

DIMENSIONS (mm)















	TECHNICAL DATA						
RATED OPERATING CONDITIONS							
Supply Voltage	r						
Temperature	85253 V ac/dc or 2040 V ac/dc						
Humidity	Ambient: 02350 °C; Storage: -2070°C						
-	< 85% without condensation						
Operating Position	Any	FAMENTO					
SAFETY AND COMPATIBILITY REQUIREMENTS							
Electromagnetic Compatibility	Noise immunity acc. to EN 61000-6-2						
	Noise emissions acc. to EN 61000-6-4						
Pollution level	Level 2 acc. to EN 61010-1						
Installation category	Cat. III acc. to EN 61010-1						
Maximal phase-to-earth operating voltage		Input circuits: 50 V acc. to EN 61010-1					
	INPUT						
Туре	Range	Error					
PT100	-200850 °C	0.2%					
PT1000	-200850 °C	0.2%					
Fe-CuNi (J)	-1001200 °C	0.3%					
Cu-CuNi (T)	-100400 °C	0.3%					
NiCr-NiAl (K)	-1001372 °C	0.3%					
PtRh10-Pt (S)	01767 °C	0.5%					
PtRh13-Pt (R)	01767 °C	0.5%					
PtRh30-PtRh6 (B)	2001767 °C	0.5%					
NiCr-CuNi (E)	-1001000 °C	0.3%					
NiCrSi-NiSi (N)	-1001300 °C	0.3%					
Chromel-kopel (L)	-100800 °C	0.3%					
Current channels (I)	0/420 mA	0.2% +/-1 digit					
Voltage channels (U)	05/10 V	0.2% +/-1 digit					
Binary	Voltageless						
	OUTPUT						
Туре	Properties	Load Capacity					
Relay (voltageless)	NO contacts	2 A/ 230 V ac					
OC open-collector	0/5 V	Max. 40 mA					
Continuous voltage	010 V	$R_{load} \ge 1k\Omega$					
Continuous current	0/420 mA	R _{load} ≤ 500Ω					
Transducer supply output	24 V dc	Max. 30 mA					
	DIGITAL INTERFACE						
Interface type	RS-485						
Protocol	Modbus RTU 8N2, 8E1, 8O1, 8N1						
Baud rate	4.8, 9.6, 19.2, 38.4, 57.6 kbit/s						
EXTERNAL FEATURES							
Readout field 2 x 4 digits; Digit height: 10 mm; Colors: red and green							
Overall dimensions	48 x 96 x 93 mm						
Weight	< 0.2 kg						
Protection grade	From frontal side: IP65; From rear side: IP20						
Bargraph	2 x 21 points; Colors: red and green						
·· J· ∽F··	poto, oo.o.o. roa ana ;	g · ·					







OTHER CONNECTIONS					
POWER SUPPLY	ADDITIONAL ANALOG INPUT SIGNAL				
17 18	0/420 mA				
BINARY INPUT 1 AND 2	CURRENT TRANSFORMER INPUT				
13 11 12 10 OU2 OU1	Current 7				
RS-485 INTERFACE	TRANSDUCER SUPPLY 24V				
B (-) 16 RS-485 A (+) 15	26 27 +				







ORDERING CODES	UC-820				
Group Designation	UC820	.1	3	1	.1
Universal process controller	UC820				
Output 1					
Relay		.1			
OC open-collector (0/5 V)		.2			
Continuous current (0/420 mA)		.3			
Continuous voltage (010 V)		.4			
Output 2					
Relay 1)			1		
OC open-collector (0/5 V)			2		
Continuous current (0/420 mA)			3		
Continuous voltage (010 V)			4		
Transducer Supply 24 V					
None				0	
Supply for transducers 24 V dc 1 W				1	
Power Supply					
85253 V ac/dc	<u> </u>				.1
2040 V ac/dc	·				.2

¹⁾ Only when a relay or OC voltage output is selected on output 1.